

# RGB DMX Stick CW4 Controller



## Specifications

<b>Input Power</b>	5-10V DC (0.6A)
<b>Output</b>	DMX512
<b>Mobile App Control</b>	<ul style="list-style-type: none"><li>• Easy Remote Pro (iOS, Android)</li><li>• Lightpad App (iOS, Android)</li></ul>
<b>Programming Software</b>	<ul style="list-style-type: none"><li>• ESA2 (Windows/Mac; Full Programming)</li><li>• Easy Remote Pro (iOS, Android; Limited Programming)</li></ul>
<b>Custom Scene Count</b>	up to 36
<b>Fixture Control Count</b>	up to 340
<b>Product Color</b>	Black
<b>Connectivity</b>	WiFi (for app control), Mini USB, 8 Dry Contact Ports, Open Drain Output (for relay)
<b>Memory</b>	Built-In Flash
<b>Mounting</b>	Single or Double-Gang Wall Socket
<b>Ambient Temperature</b>	14°F to 113°F (-10°C to 45°C)
<b>Dimensions (WxHxD)</b>	4-3/16" x 5-3/4" x 3/8" (146mm x 106mm x 10mm)
<b>Weight</b>	7 oz. (200g)
<b>Certifications</b>	EC, EMC, RoHS
<b>Environment</b>	Indoor, Dry
<b>Warranty</b>	5 Year Limited



### Easy Control Pro



### Lightpad App



### ESA2 Software

Available for Windows & Mac

## Ordering

<b>Part Number</b>	RGB-DMX-CONT-STICK-CW4
<b>Package Contents</b>	<ul style="list-style-type: none"><li>• RGB DMX Stick CW4 Controller</li><li>• 5-10V DC Power Supply with AC Plug</li><li>• Mini USB Cable</li><li>• Installation Instructions</li></ul>