

# DIMMER COMPATIBILITY LIST

for HYBRID MLV/INCANDESCENT DRIVERS



web: [www.LEDI.LIGHTING](http://www.LEDI.LIGHTING)

phone: (832)-717-2710

email: [designs@ledinspirations.com](mailto:designs@ledinspirations.com)

address: 11744 Grant Rd. Cypress, TX 77429



## LOAD REQUIREMENTS FOR HYBRID MLV/INCANDESCENT DIMMABLE DRIVERS

Driver Part #	C•L or CFL/LED Dimmer Minimum Load Required	MLV and/or Incandescent Dimmer Minimum Load Required
DR-20W-24VDC-120V-2-MLV-m	8 Watts	50% (10 Watts)
DR-40W-24VDC-120V-2-MLV-m	8 Watts	50% (20 Watts)
DR-60W-24VDC-120V-2-MLV-m	8 Watts	50% (30 Watts)
DR-96W-24VDC-120V-2-MLV-m	8 Watts	50% (48 Watts)

**WARNING: DO NOT EXCEED THE MAXIMUM LOAD CAPACITY OF AN LED DRIVER.**

## INTRODUCTION

All of the dimmers listed below have been tested by LEDI. Please note that any dimmers not listed on this Dimmer Compatibility List may not have been tested by LEDI. Have questions about a dimmer that isn't listed below? Please contact LEDI's Serve Team for assistance at (832)-717-2710 or [designs@ledinspirations.com](mailto:designs@ledinspirations.com).

## LUTRON DIMMERS

Dimmer Model	Compatible Part #'s	Dimming Type	Minimum Load Requirement	Dimming Range (Lumen Output)
<b>Diva C•L</b>	#DVCL-153P, #DVCL-153PH, #DVCL-253P, #DVSCCL-153P, #DVSCCL-253P	C•L or CFL/LED	8 Watts	100% - .01%
<b>Maestro C•L</b>	#MACL-153M, #MSCL-OP153M	C•L or CFL/LED	8 Watts	100% - 1%
<b>Lumea C•L</b>	#LECL-153P	C•L or CFL/LED	8 Watts	100% - 1%
<b>Ariadni/Toggler C•L</b>	#AYCL-153P	C•L or CFL/LED	8 Watts	100% - .01%
<b>Maestro (Incandescent)</b>	#MA-600, #MA-1000, #MSC-600M, #MSC-1000M	Incandescent	50%	100% - .01%
<b>Caseta Wireless</b>	#PD-5NE	Incandescent/MLV	50%	100% - .01%
<b>Skylark (MLV)</b>	#SLV-600P	MLV	50%	100% - .01%

## LEVITON DIMMERS

Dimmer Model	Compatible Part #'s	Dimming Type	Minimum Load Requirement	Dimming Range (Lumen Output)
<b>Decora Universal</b>	#DSM10-1LZ	Incandescent/MLV	50%	100% - 5%
<b>Decora Smart</b>	#DW6HD-1BZ	Incandescent	50%	100% - .01%
<b>Decora SureSlide</b>	#6674-POW	Incandescent/MLV	50%	100% - .01%

## LEGRAND DIMMERS

Dimmer Model	Compatible Part #'s	Dimming Type	Minimum Load Requirement	Dimming Range (Lumen Output)
<b>adorne softTap</b>	#ADTP700MTU	Incandescent/MLV	50%	100% - .01%
<b>adorne Paddle</b>	#ADPD453L	Incandescent	50%	100% - 7%
<b>Radiant Paddle</b>	#RHCL453PW	Incandescent	50%	100% - 4%

## GE DIMMERS

Dimmer Model	Compatible Part #'s	Dimming Type	Minimum Load Requirement	Dimming Range (Lumen Output)
<b>Z-Wave Plus Wireless</b>	#14294	Incandescent	50%	100% - .01%